

VENGA SURFACE MOUNTED SERIES



This product must be installed in accordance to the national electrical code and all applicable local codes. Failure to do so may result in serious injuries. Proper grounding is required for safety. Do not install if product appears to be damaged.




Included Hardware:

- A: Luminaire
- B: Lens
- C: Endcap
- D: Endcap Screws
- E: Installation Kit (Optional)

Required Tools and Hardware:

- Driver
- Laser Line Level
- Level
- Drill
- Drywall Cutting Tool
- Screwdriver
- Pen
- Wire Connectors
- Screws
- Anchors (If Necessary)

VENGA SURFACE MOUNTED SERIES

 This product must be installed in accordance to the national electrical code and all applicable local codes. Failure to do so may result in serious injuries. Proper grounding is required for safety. Do not install if product appears to be damaged.



Instructions:

- 1** Turn power off.
- 2** Install *Driver* in desired location and bring power cord to the location of *Luminaire* (A).
- 3** Measure and mark location of *Luminaire* (A) as well as pre-drilled holes.
- 4** Prepare access to main power lines as needed.
- 5** Using *Wire Connectors*, connect the stripped cables to *Driver*.
- 6** If *Installation Kit* (E) is being used, screw *Pass-Through Set Screw* into *Pass-Through Wire*. Do NOT damage power cord.
- 7** Securely screw *Luminaire* (A) level to the surface through pre-drilled holes and using *Anchors* if necessary. Do NOT damage light source.
- 8** Insert **OR** clip *Lens* (B) into topmost groove depending on model ordered.
- 9** Screw *Endcap* (C) to *Luminaire's* (A) extremity using *Endcap Screws* (D).
- 10** Turn power on.



Do not overload power unit if many *Luminaires* are connected to the same one.

